

Bose Amplifier Wiring for AMP Bypass

Connector Harness

9	10	11	12	13	14	15	16	17	18	19	20
21	22	23	24	25	26	27	28	29	30	31	32

BOSE Inputs and Outputs listed by corresponding speaker

FUNCTION		PIN	WIRE COLOR	FUNCTION		PIN	WIRE COLOR
Right Rear -	Input	23	PINK	Right Rear -	Output	16	BLACK
Right Rear +	Input	24	BLUE	Right Rear +	Output	15	BROWN
Left Rear -	Input	25	VIOLET	Left Rear -	Output	14	BLACK/YELLOW
Left Rear +	Input	26	LIGHT GREEN	Left Rear +	Output	13	GREEN/YELLOW
Right Front -	Input	27	WHITE/BLUE	Right Front -	Output	20	YELLOW*
Right Front +	Input	28	ORANGE/BLUE	Right Front +	Output	19	GRAY*
Left Front -	Input	29	ORANGE	Left Front -	Output	18	RED*
Left Front +	Input	30	WHITE	Left Front +	Output	17	GREEN*

*The front door tweeters are wired in parallel with the front door woofers

BOSE Inputs and Outputs listed by PIN Order

FUNCTION		PIN	WIRE COLOR	FUNCTION		PIN	WIRE COLOR
Left Rear Spkr +	Output	13	GN/YW	Right Rear -	Input	23	PK
Left Rear Spkr -	Output	14	BK/YW	Right Rear +	Input	24	BU
Right Rear Spkr +	Output	15	BN	Left Rear -	Input	25	VT
Right Rear Spkr -	Output	16	BK	Left Rear +	Input	26	L.GN
Left Front Spkrs +	Output	17	GN*	Right Front -	Input	27	WT/BU
Left Front Spkrs -	Output	18	RD*	Right Front +	Input	28	OG/BU
Right Front Spkrs+	Output	19	GY*	Left Front -	Input	29	OG
Right Front Spkrs -	Output	20	YW*	Left Front +	Input	30	WT

Amp Remote		31	L.BU
------------	--	----	------